6 Ways DMX Signal Splitter

Model No.: DMA2X3

Input and output optical isolation/Six independent outputs/DMX512-A compatible



CE RoHS emc LVD

Features

- Two DMX512 signal input, repeat 2 x 3 DMX512 signal output, each allowing for 32 DMX devices to be connected.
- Dedicated to amplify, distribute and insulate the signal that comes from the lighting system equipment when it is connected to the bus of DMX512(or RS-485).
- Photo-electricity insulation between input and output terminals, output terminals among channels.
- Input isolated from outputs to 500VAC, 1000VDC.
- Outputs are isolated from each other to 500VAC, 1000VDC.
- Input and outputs are ture RS-485 rated, and no microprocessors are used for maximum reliability.
- 9 LEDs indicate power in, DMX in and DMX output status.

Technical Parameters


| Input and Output | |
|------------------|------------|
| Input voltage | 12-48VDC |
| Input current | 0.5A Max. |
| Input signal | DMX512 x 2 |
| Output signal | DMX512 x 6 |


| Environment | |
|-------------------------|-----------------|
| Operation temperature | Ta:-30°C ~+55°C |
| Case temperature (Max.) | Tc:+85°C |
| IP rating | IP20 |

| Safety and EMC | |
|----------------------|---|
| EMC standard (EMC) | EN55032:2015, EN61000-3-2:2014, EN61000-3-2:2013, EN55024:2010/A1:2015 |
| Safety standard(LVD) | EN 61347-1:2015 EN 61347-2-11:2015 |
| Certification | CE,EMC,LVD |

| Warranty and Protection | | |
|-------------------------|------------------|--|
| Warranty | 5 years | |
| Protection | Reverse Polarity | |

Mechanical Structures and Installations






User Manual Ver 1.0.0 Page 1

Wiring Diagram

DMX 512 Mater



Note:

- 1. A passive loop-through connection allows onward connection to other DMX512 devices. If this feature is not required then the signal must be terminated.
- 2. Each output is capable of driving 32 additional DMX512 devices.

 It is not necessary to terminate any outputs that are not connected.

 However, a terminator must be connected to the final DMX512 device.
- 3. Connect 0.25W 90-120 Ω terminal resistor for termination.

User Manual Ver 1.0.0